

Fuse plug - PV-C-M/F-PRO/F-1000/8-EU - 1622153

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)



Fuse connector for protecting modules and devices in photovoltaic systems, black, SUNCLIX pin connector pattern, 1000 V/8 A, IP68 (24 h/2 m)

SUNCLIX fuse connector, in the version for 1000 V system voltage


Product Description

SUNCLIX fuse connector, for 1000 V system voltage, fuse-link nominal current of 8 A, EU version

Why buy this product

- One-piece design
- Robust, easy-to-install fuse element for outdoor use
- High-quality fuse-link
- Degree of protection: IP68 (24 h/2 m)
-
- 1000 V (EN)

Key Commercial Data

Packing unit	8 STK
Minimum order quantity	8 STK
GTIN	 4 055626 130750
GTIN	4055626130750

Technical data

Ambient conditions

Degree of protection (when plugged in)	IP66 / IP68 (2 m / 24 h)
Ambient temperature (operation)	-40 °C ... 50 °C

General

Rated voltage	1000 V
Fuse-link nominal current	8 A DC (Nominal current of the fuse-link)
Fuse adapter nominal current	8 A DC

Fuse plug - PV-C-M/F-PRO/F-1000/8-EU - 1622153

Technical data

Material

Flammability rating according to UL 94	V0
--	----

Standards and Regulations


Flammability rating according to UL 94	V0
--	----

Environmental Product Compliance

China RoHS	Environmentally friendly use period: unlimited = EFUP-e
	No hazardous substances above threshold values

Drawings

Dimensional drawing



Phoenix Contact 2018 © - all rights reserved
<http://www.phoenixcontact.com>

PHOENIX CONTACT GmbH & Co. KG
Flachsmarktstr. 8
32825 Blomberg
Germany
Tel. +49 5235 300
Fax +49 5235 3 41200
<http://www.phoenixcontact.com>